

MIRA free your EAR



1hrs battery charging /14 hrs hearing aid mode
/2 hrs music streaming mode/ 125/60dB & 113/53dB

Use MIRA for the ultimate experience in remote control. Sound adjust, listen programmes change and switch to audio streaming- all without reaching for your hearing aid.

Get better sound quality with MIRA ANR,AFC and ADM technology.
Hear more all you want, less of what you don't.

www.retone-hearing.com



Detachable & rechargeable battery



Audio streaming



Automatic call answer & out



Bluetooth V4.0

Enable with



Android



iPhone



iPad

Make your own brand Bluetooth hearing aid in 3 steps & 6 months

Step 1 You describe idea
color ?function? RIC?

Step 1 We build prototype
Housing/APP/Function customized

Step 1 Mass production & Verify
sourcing/market/dynamic control



At a glance

Feature

	MIRA 200 400 600	MIRA 202 402 602
Processing	200: 2CH, 400: 4CH, 600:6CH	00: 2CH, 400: 4CH, 600:6CH
Housing Design	BTE	Open-fit
Volume control	Remote control	Remote control
Switch & trimmer	Memory switch & Remote control	Memory switch & Remote control
Programmable	400/600: v	402/602: v

Measurement

Peak OSPL90(dB SPL)	124	120
OSPL90-HFA(dB SPL)	117	110
Peak Gain(dB)	58	35
HFA/FOG(dB)	50	25
Reference Test Gain(dB)	40	26
Frequency Range(Hz)	400-4200	200-4200
Harmonic Distortion		
@500Hz(%)	1.0	1.0
@800Hz(%)	2.2	1.0
@1600Hz(%)	1.0	1.0
EQ Input NOISE(dB)	25	30
Battery Size	Recharge battery	Recharge battery
Battery Current (mA)	3.0	3.0

/IEC118-7/94 (HA2-2CC Coupler) Data may be subject to change with product refinement